CLAXARENA, CLAXARENASBS01 CLAXARENASBS05, CLAXARENASBS10

ARENA AX - BACnet Supervisor



OVERVIEW

ARENA^{AX} is a BACnet certified web-based supervisor utilizing the Niagara^{AX} Framework[®] for small to big size systems.

It is used to supervise HVAC systems and non-HVAC systems (e.g. lighting, security, life safety) in a building or across multiple buildings. The primary use is in applications where multiple HAWK and/or EAGLE controllers are networked together and systems based on TCP/IP communication standards like BACnet / IP, oBIX, OPC (client), Modbus TCP, EIB-KNX/IP, and SNMP can be directly integrated by ARENA^{AX}.

ARENA^{AX} serves real time graphical information to standard web-browser clients and also provides server-level functions such as: centralized data logging, archiving, alarming, real time graphical displays, master scheduling, system-wide database management, and integration with enterprise software applications.

In addition, it provides a comprehensive, graphical engineering toolset for application development.

ARENA^{AX} helps to maximize operating and services opportunities and to minimize associated costs.

ENGINEERING

The graphical engineering tool (COACH AX) is embedded in the ARENA $^{\rm AX}$ system.

FEATURES

- WEB ACCESS Access to alarms, logs, graphics, schedules, and configuration data with a standard web browser and mobile devices
- GRAPHICS Java-enabled user interface (UI) as well as non-Java UI for browsers
- ALARMING Sophisticated alarm processing and routing, including email/sms alarm acknowledging
- INTEGRATION
 Optional direct ethernet-based driver support for BACnet

Product Data

I/P, OPC (client), Modbus TCP, EIB/IP and SNMP; additional points for each driver can be purchased in blocks of 500 for each protocol

USERS

Supports an unlimited number of users over the Internet / Intranet with a standard web browser, depending on the host PC resources

ARCHIVING

Optional enterprise-level data archival using SQL, MySQL, CSV, Oracle or DB2 database, and HTTP/HTML/XML text formats.

AUDIT

"Audit Trail" of database changes, database storage and backup, global time functions, calendar, central

SECURITY

Password protection and security using standard Java (on Windows platforms only) authentication and encryption techniques with optional security supported via an external LDAP connection

CONTROLLER

Supports multiple HAWK stations and EAGLE controllers connected to a local Ethernet network, or the Internet

HELP

HTML-based help system that includes comprehensive online system documentation

- VERSIONS
 Different "Small Building System" versions are available for up to five and up to ten HAWKs and /or EAGLE controller
- BACNET
 BACnet OWS and AWS certified version available

PLATFORM REQUIREMENTS

Processor	Intel Pentium™ IV, 2 GHz or higher, Core 2 Duo also acceptable
Operating System	 Windows XP Professional (SP3, 32-bit) Windows Server 2012 Standard/Enterprise (SP2, 64-bit) (R2 as well)
	 Windows 7 Professional/Enterprise/Ultimate (32-bit and 64 bit)
	 Windows 8 Professional/Enterprise/Ultimate (32-bit and 64 bit) Windows 8.1 Professional/Enterprise/Ultimate (64-bit)
	• VMware - ESXi 5.1.0
	Microsoft Virtual Server 2008
Memory	1 GB minimum 2 GB recommended for large systems, 8 GB or more recommended for Win 64 bit

version



Hard Drive	1 GB minimum 5 GB for applications that need more archiving capacity
Display	Video card and monitor capable of displaying 1024 x 768 pixel resolution or greater
Network Support	Ethernet adapter (10/100 Mb with RJ-45 connector)
Connectivity	Full time high speed ISP connection recommended for remote site access (i.e. T1, ADSL, cable modem)

WHAT TO ORDER

ARENA^{AX} order numbers:

CLAXARENA	ARENA ^{AX}
CLAXARENAAPC	Alarm Portal
CLAXARENASBS01	Single Station version with a limit of 1 HAWK (supports only 500 points for add-on drivers, not BACnet certified)
CLAXARENASBS05	BACnet OWS certified Small Building System version with a limit of 5 HAWKs and 5 EAGLEs
CLAXARENASBS10	Small Building System version with a limit of 10 HAWKs and 10 EAGLEs (not BACnet certified, BACnet certification can be achieved by adding CLAXDRBACOWS)

Optional ARENA^{AX} database drivers for external database applications:

CLAXDBSQL	MS-SQL Database driver
CLAXDBMYSQL	MYSQL Database driver
CLAXDBCSV	CSV Server driver
CLAXDBDB2	DB2 Database driver
CLAXDBORCL	Oracle Database driver


ARENA^{AX} upgrades:

CLAXARENARUP	Upgrade to latest Niagara version
CLAXARENASBSU5	Upgrade SBS05 to SBS10
CLAXARENASBSUP	Upgrade SBS10 to Full ARENAAX

Optional ARENA^{AX} open system drivers:

CLAXDRBACOWSBACnet Operator Workstation includes 500 points for ARENA AXCLAXDRBACAWSAdditional BACnet AWS featureCLAXDRBACEXPAdditional BACnet Server Export featureCLAXDRBAC500Additional 500 BACnet pointsCLAXDREIBEIB-IP driver with 500 pointsCLAXDREIBDriver with additional 500 EIP-IP driver pointsCLAXDRLONIPLONIP driver with 500 pointsCLAXDRLONIP500Driver with additional 500 LONIP pointsCLAXDRMTCPModbus driver TCP with 500 pointsCLAXDROBXOBIX driver with 500 pointsCLAXDROBXOBIX driver with 500 pointsCLAXDROPCOPC driver with 300 pointsCLAXDROPCOPC driver with 500 pointsCLAXDRSNMPSNMP driver with 500 pointsCLAXDRSNMPDriver with additional 500 SNMP pointsCLAXARENAAXIAdditional 4 Cameras Axis video driverCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENAADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENAARE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAAMIL4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Additional 4 CamerasCLAXARENAMIL4Additional 4 CamerasCLAXARENAMIL4Additional 4 CamerasCLAXARENAMIL4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Additonal 4 Cameras Milestone NVM video driver		
CLAXDRBACEXPAdditional BACnet Server Export featureCLAXDRBAC500Additional 500 BACnet pointsCLAXDREIBEIB-IP driver with 500 pointsCLAXDREIB500Driver with additional 500 EIP-IP driver pointsCLAXDRLONIPLONIP driver with 500 pointsCLAXDRLONIP500Driver with additional 500 LONIP pointsCLAXDRMTCPModbus driver TCP with 500 pointsCLAXDROBXOBIX driver with 500 pointsCLAXDROBXOBIX driver with 500 pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPC500Driver with additional 500 oDIXCLAXDRSNMPSNMP driver with 500 pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENAAEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENAAEDAdd 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driver 16 CamerasCLAXARENAARIAAdd 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Additional 4 Cameras Honeywel RapidEye NVM video driver	CLAXDRBACOWS	
TeatureCLAXDRBAC500Additional 500 BACnet pointsCLAXDREIBEIB-IP driver with 500 pointsCLAXDREIB500Driver with additional 500 EIP-IP driver pointsCLAXDRLONIPLONIP driver with 500 pointsCLAXDRLONIP500Driver with additional 500 LONIP pointsCLAXDRMTCPModbus driver TCP with 500 pointsCLAXDROBXOBIX driver with 500 pointsCLAXDROBXOBIX driver with 500 pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPCOPC driver with 500 pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMPDriver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Additional 4 Cameras NetVu DVR video driver	CLAXDRBACAWS	Additional BACnet AWS feature
CLAXDREIBEIB-IP driver with 500 pointsCLAXDREIB500Driver with additional 500 EIP-IP driver pointsCLAXDRLONIPLONIP driver with 500 pointsCLAXDRLONIP500Driver with additional 500 LONIP pointsCLAXDRMTCPModbus driver TCP with 500 pointsCLAXDROBXDriver with additional 500 ModbusTCP pointsCLAXDROBXOBIX driver with 500 pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPCOPC driver with 500 pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMPSNMP driver with 300 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENAAEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENAHREHoneywel RapidEye NVM video driver 16 CamerasCLAXARENAMIE4Additional 4 Cameras Honeywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driver 16 Cameras	CLAXDRBACEXP	
CLAXDREIB500Driver with additional 500 EIP-IP driver pointsCLAXDRLONIPLONIP driver with 500 pointsCLAXDRLONIP500Driver with additional 500 LONIP pointsCLAXDRMTCPModbus driver TCP with 500 pointsCLAXDRMTCP500Driver with additional 500 ModbusTCP pointsCLAXDROBXoBIX driver with 500 pointsCLAXDROBXDriver with additional 500 oBIX pointsCLAXDROBXDriver with additional 500 oBIX pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPC500Driver with additional 500 OPC pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMPDriver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENAAEHoneywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driver 16 CamerasCLAXARENAMIL4Add Cameras Milestone NVM	CLAXDRBAC500	Additional 500 BACnet points
driver pointsCLAXDRLONIPLONIP driver with 500 pointsCLAXDRLONIP500Driver with additional 500 LONIP pointsCLAXDRMTCPModbus driver TCP with 500 pointsCLAXDRMTCP500Driver with additional 500 ModbusTCP pointsCLAXDROBXoBIX driver with 500 pointsCLAXDROPCOPC driver with additional 500 oBIX pointsCLAXDROPC500Driver with additional 500 oPC pointsCLAXDROPC0OPC driver with 500 pointsCLAXDROPC500Driver with additional 500 OPC pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENAADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENAPAdd 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHREAdditional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMILMilestone NVM video driver 16 Cameras	CLAXDREIB	EIB-IP driver with 500 points
CLAXDRLONIP500Driver with additional 500 LONIP pointsCLAXDRMTCPModbus driver TCP with 500 pointsCLAXDRMTCP500Driver with additional 500 ModbusTCP pointsCLAXDROBXoBIX driver with 500 pointsCLAXDROBX500Driver with additional 500 oBIX pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPC500Driver with additional 500 OPC pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMP500Driver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENAAEHAdd 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMILMilestone NVM video driver 16 CamerasCLAXARENAMIL4Add 4 Cameras Milestone NVM	CLAXDREIB500	
pointsCLAXDRMTCPModbus driver TCP with 500 pointsCLAXDRMTCP500Driver with additional 500 ModbusTCP pointsCLAXDROBXoBIX driver with 500 pointsCLAXDROBX500Driver with additional 500 oBIX pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPC500Driver with additional 500 OPC pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMP500Driver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Honeywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Milestone NVM video driver 16 CamerasCLAXARENAMIL4Add 4 Cameras Minestone NVM	CLAXDRLONIP	LONIP driver with 500 points
CLAXDRMTCP500Driver with additional 500 ModbusTCP pointsCLAXDROBXoBIX driver with 500 pointsCLAXDROBX500Driver with additional 500 oBIX pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPC500Driver with additional 500 OPC pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMP500Driver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAHRE4Honeywel RapidEye NVM video driverCLAXARENAMIL4Add 4 Cameras Honeywel RapidEye NVM video driver	CLAXDRLONIP500	
ModbusTCP pointsCLAXDROBXoBIX driver with 500 pointsCLAXDROBX500Driver with additional 500 oBIX pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPC500Driver with additional 500 OPC pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMP500Driver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Additonal 4 Cameras Honeywel RapidEye NVM video driver	CLAXDRMTCP	Modbus driver TCP with 500 points
CLAXDROBX500Driver with additional 500 oBIX pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPC500Driver with additional 500 OPC pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMP500Driver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Add 4 Cameras Milestone NVM	CLAXDRMTCP500	
pointsCLAXDROPCOPC driver with 500 pointsCLAXDROPC500Driver with additional 500 OPC pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMP500Driver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Add 4 Cameras Milestone NVM	CLAXDROBX	oBIX driver with 500 points
CLAXDROPC500Driver with additional 500 OPC pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMP500Driver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Honeywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Add 4 Cameras Milestone NVM	CLAXDROBX500	
pointsCLAXDRSNMPSNMP driver with 500 SNMP pointsCLAXDRSNMP500Driver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Honeywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Add 4 Cameras Milestone NVM	CLAXDROPC	OPC driver with 500 points
CLAXDRSNMP500Driver with additional 500 SNMP pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Honeywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Add 4 Cameras Milestone NVM	CLAXDROPC500	
pointsCLAXARENAAXIAxis Cameras video driver 16 CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Honeywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Milestone NVM video driver 16 Cameras	CLAXDRSNMP	SNMP driver with 500 SNMP points
CamerasCLAXARENAAXI4Additional 4 Cameras Axis video driverCLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHRE4Honeywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Milestone NVM video driver 16 Cameras	CLAXDRSNMP500	
CLAXARENADEDDed. Micros NetVu DVR driver 16 CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHREHoneywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMIL4Milestone NVM video driver 16 Cameras	CLAXARENAAXI	
CamerasCLAXARENADED4Add 4 Cameras Ded. Micros NetVu DVR video driverCLAXARENAHREHoneywel RapidEye NVM video driver 16 CamerasCLAXARENAHRE4Additional 4 Cameras Honeywel RapidEye NVM video driverCLAXARENAMILMilestone NVM video driver 16 CamerasCLAXARENAMIL4Add 4 Cameras Milestone NVM	CLAXARENAAXI4	
DVR video driver CLAXARENAHRE Honeywel RapidEye NVM video driver 16 Cameras CLAXARENAHRE4 Additional 4 Cameras Honeywel RapidEye NVM video driver CLAXARENAMIL Milestone NVM video driver 16 Cameras CLAXARENAMIL4 Add 4 Cameras Milestone NVM	CLAXARENADED	
driver 16 Cameras CLAXARENAHRE4 Additional 4 Cameras Honeywel RapidEye NVM video driver CLAXARENAMIL Milestone NVM video driver 16 Cameras CLAXARENAMIL4 Add 4 Cameras Milestone NVM	CLAXARENADED4	
RapidEye NVM video driver CLAXARENAMIL Milestone NVM video driver 16 Cameras CLAXARENAMIL4 Add 4 Cameras Milestone NVM	CLAXARENAHRE	Honeywel RapidEye NVM video driver 16 Cameras
Cameras CLAXARENAMIL4 Add 4 Cameras Milestone NVM	CLAXARENAHRE4	
	CLAXARENAMIL	
	CLAXARENAMIL4	

ARCHITECTURE



Manufactured for and on behalf of the Environmental and Combustion Controls Division of Honeywell Technologies Sàrl, Rolle, Z.A. La Pièce 16, Switzerland by its Authorized Representative:

CentraLine Honeywell GmbH Böblinger Strasse 17 71101 Schönaich, Germany Phone +49 (0) 7031 637 845 Fax +49 (0) 7031 637 740 info@centraline.com www.centraline.com

Subject to change without notice EN0Z-0945GE51 R0714

